



PIXIE SMART DIMMER - SDD300BTAM G3

PIXIE MASTER DEVICE - SMART HOME push button dimmer, Generation 3 with Bluetooth Mesh Technology

Application

Smart digital lighting control with Bluetooth Mesh Technology for residential and commercial spaces

Design Specifications

- Digital push button control, with three (3) complimentary key caps provided to suit most switch plates
- When used as a digital device, push on/off, hold to dim up or down, memory function, selectable minimum dim level
- When used with the SAL PIXIE or PIXIE PLUS app, set a scene, group devices, set a schedule, dim, switch, set a timer
- With the inclusion of the SAL PIXIE Gateway and the internet, you can control your PIXIE devices from anywhere in the world
- Overheating, overload and full short circuit protection, maximum load 300 watt (resistive), 250VA (capacitive LED), minimum load 2 watt* . See installation sheet for multi-gang de-rating values.
- SMART LED indicator, Trailing edge phase cutting dimming, Fits most branded switch plates. 1 to 6 gang, complies to AS/NZS 60669.2.1, typical wireless range 15 metres



Performance

- Dimmable - **YES**
- Dimmer Type - **Trailing edge**



