



# MT987 20A Micro-Ohmmeter


The MT987 is a 20A Micro-Ohmmeter, also known as transformer DC resistance tester, DC resistance quick tester, earth continuity tester. It uses microprocessor technology for testing safely, precisely and reliably. It is mainly used to measure the resistance of transformer windings, earth conductor continuity test, wire resistance of cables, switches, connectors, contact resistance of relays, coils, motors, and equipment casings, lightning protection belts, earth connection resistance test between metal components of beams, structures, cabinets, steel bars, water pipes, windows, guardrails, radiators and assembly lines. Widely used in telecommunications, electricity, meteorology, computer rooms, oil fields, power distribution lines, tower transmission lines, gas stations, factory earthing grids and lightning rods.

The MT987 is composed of monitoring software, test line and communication line. The meter has rechargeable batteries, full-colour large-screen LCD display, touch screen operation, port overload prevention function. Large capacity storage of 800 sets of data. Stored data can be transferred to a PC using an optical USB and software supplied and has the functions of reading, comparing and saving historical data. The Bluetooth function can connect with the Android App. There is a built-in printer where test results can be immediately printed for reference.

## Features

- Built-in 14.6V 12000mAh rechargeable Lithium battery
- 4 Wire test method
- 108mm x 65 mm true colour touch screen
- Maximum resolution 0.1μΩ
- Discharge probes: LCD has a built-in reminder
- Printer function
- Data storage of 800 sets
- USB interface for linking to computer
- Bluetooth function allows connection to Android devices

Function	Range	Amperage	Accuracy
Resistance	10.0μΩ – 1000.0μΩ	20A	±(0.2% FS ±10)
	1.000mΩ – 10.000mΩ	20A	±(0.2% FS ±10)
	10.00mΩ – 100.00mΩ	10A	±(0.2% FS ±10)
	1.000Ω – 10.00Ω	1A	±(0.2% FS ±10)
	10.0Ω – 100.00Ω	0.1A	±(0.2% FS ±10)
	100.0Ω – 1000.0Ω	10mA	±(0.2% FS ±10)
	1.000kΩ – 10.00kΩ	1mA	±(0.4% FS ±30)
	10.00kΩ – 100.00kΩ	1mA	±(0.4% FS ±30)
	100.0kΩ – 1000.0kΩ	1mA	±(1% FS ±30)
Temperature	-10°C to 60°C		±1.0°C
Detection	4-Wire test		
Method			
Shutdown	Auto: 5, 10, 15, 20, 25,30min / Optional OFF		
Measuring Time	About 2 seconds		
Batteries	3.7V Lithium - Rechargeable Batteries		
Dimensions	277 x 277 x 153mm		
Weight	3.1kg		



True Colour Touch Display



Voltage & Current Terminals



Printer

## MT987 | 20A Micro-Ohmmeter

Contact Us  
South Africa

[www.major-tech.com](http://www.major-tech.com) [sales@major-tech.com](mailto:sales@major-tech.com)

Australia

[www.majorotech.com.au](http://www.majorotech.com.au) [info@majorotech.com.au](mailto:info@majorotech.com.au)