

# ROBUS®

**BARON2 LED BATTEN, IP20, CCT3 SELECTABLE 3000K  
4500K 6500K, WHITE**

**RBNX06CCT3-01, RBNX12CCT3-01**

PLEASE READ INSTRUCTION BEFORE COMMENCING INSTALLATION AND RETAIN FOR FUTURE REFERENCES.

! Electrical products can cause death or injury, or damage to property. The Installation must be carried out by a qualified electrician. Product or a person falling from height can cause serious personal injury. Please ensure suitable equipment is used by a competent person.

Note:

The luminaire must be disconnected before carrying out any insulation resistance testing. Product technical information and specification may change over time without prior notification. For the latest technical information please visit our web site [www.robust.com.au](http://www.robust.com.au)

-20°C < Ta < +40°C, 220-240V ~ 50Hz, Class I, IP20

Luminaire is non-dimmable.

Suitable for mounting on a normally flammable surface.

## Installation

1. Ensure mains supply is switched off before commencing work.
  2. Use the flathead screwdriver to unlock and pull the end cover out.
  3. Pull the diffuser off along the track and remove the diffuser.
  4. Mark appropriate fixing points on wall or ceiling; check that fixings will not impinge on concealed cables or pipes before drilling holes. Insert the wall plug and fix two brackets onto the wall using the screws.
  5. Feed supply power cables through the cable hole to connect the fitting terminal: Brown/Live to L, Neutral/Blue to N and Earth/Green Yellow to E. Then fix the cables onto the restrained block.
  6. Attach the fitting to the brackets until it is secure.
  7. Choose the CCT and the wattage at the end of fitting moving the switches. CCT colour temperature selectable (3000K, 4000K or 6500K). RBNXCCT306-01: 10W or 20W. RBNXCCT312-01: 20W or 40W.
- WARNING: DO NOT CHANGE CCT AND WATTAGE WHEN THE FITTING IS ON!!**

This product has no user serviceable parts. If any part is damaged, disconnect from mains and discontinue use

**The Installation must be carried out by a qualified electrician**

LED Group Australia Pty Limited  
Suite B, 2 Pittwin Road  
Capalaba  
Queensland 4157  
Australia  
Tel: 07 3890 5444  
Fax: 07 3890 4777  
Email: [purchases@robust.com](mailto:purchases@robust.com)  
Website: [www.robust.com.au](http://www.robust.com.au)



LED Group  
Crowe Horwath  
72 Trafalgar Street  
NELSON 7010  
New Zealand  
Tel: +64 3668 5285  
Email: [nz\\_purchases@robust.com](mailto:nz_purchases@robust.com)  
Website: [www.robustled.co.nz](http://www.robustled.co.nz)

Issue 1 310724

