

29-31 Richland St. Kingsgrove. Sydney NSW 2208 Australia Phone: 1300 236 687 | Fax: 02 9554 9433

enquiries@domuslighting.com.au | www.domuslighting.com.au

## Installation Manual

Date: August 12, 2025 11:19 AM

## **BLAZE-PRO-24V Series**


C	. [	ications
<b>3</b> p	ecin	lcations
-		

	50W	100W		
Power:	20/30/50W	100W		
CCT:	3000K/4000K/5500K	3000K/4000K/5500K		
Lumen (±5%):	5148/5846/5387lm	11490/12194/11666lm		
Net Weight:	0.72kg	1.28kg		
Max Projected Area:	0.020m <sup>2</sup>	0.045m <sup>2</sup>		
Dimmable:	No	IP Rating:	IP66	
Input Voltage:	24V	Beam Angle:	120°	
CRI:	≥70	Lifespan:	20,000hrs	
CCT (Switchable):	3000K- 4000K-5500K	Power Factor:	≥1.0	
Warning: Low Voltage Model – 24V DC Constant Voltage LED Driver Required				

## CCT and Power selectable by DIP switch



Use Allen key (5mm) to unscrew the dip switch CCT and power selectable waterproof cover.



Toggle the switch to the desired colour temperature and power. (Please note don't operate the switch while power is on.)



Use Allen key (5mm) to tighten screw on the waterproof ring and cover.