

ROBUS®

VEGAS COB 7W/M, 24V, LED STRIP LIGHT KIT, CCT3 SELECTABLE (2700K/4000K/6000K)

R2MCOBSIK-CCT3 R5MCOBSIK-CCT3

PLEASE READ INSTRUCTION BEFORE COMMENCING INSTALLATION AND RETAIN FOR FUTURE REFERENCES.

! Electrical products can cause death or injury, or damage to property. If in any doubt about the installation or use of this product, consult a competent electrician

Note:

Product technical information and specification may change over time without prior notification. For the latest technical information please visit our web site <https://au.robus.com>

-20°C < Ta < +40°C, 220-240V~50Hz, Class II, the strip is IP44 and the rest of the components is IP20.

Suitable for mounting on a normally flammable surface.

Installation

1. Ensure mains supply is switched off before commencing work.
2. Cut the LED Strip to the required length at the locations marked on the strip (Every 30mm). Note: The IP rating cannot be guaranteed when cut to expose the copper plate and total power of LED strips that extended cannot be over than the power of current driver.
3. Mounting the Strip: Clean the surface you desired, in which is dry, flat and free of any debris; Self-adhesive strip: Remove the protective film to reveal adhesive strip. Place the strip onto the desired location and press down firmly. Ensure the strip is secure.
4. Connect to CCT3 switch and driver by the quick fix connector. Note: Please place the driver, CCT3 switch and the quick fix connector into suitable enclosure to enhance their existing rating to IP44.
5. Insert plug into mains socket. Choose the colour temperature (2700K, 4000K or 6000K) by pressing the CCT3 switch.

Accessory:

R2MEC: VEGAS COB 2M extension cable with barrel jacks.

Note:

1. Please take care not to damage the LEDs, during installation. The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced. If the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or his service agent or a similar qualified person in order to avoid a hazard.
2. Do not connect the chain to the supply while it is in the packing/on reels.
3. Do not interconnect parts of this light chain with parts of another manufacturer's lighting chain.
4. Do not pull light by supply cable; Fragile; Handle with care.
5. Do not touch the LEDs with bare hands. Use clean, soft, antistatic gloves and ensure not to apply excessive pressure on LED's during Strip installations.
6. Do not stare at the operating light source for prolonged period.
7. Do not hang, sag or loose fit Power supply / control units and its accessories including LED Strips.

The Installation must be carried out by a qualified electrician

LED Group Australia Pty Limited
Unit 3, 2 Pittwin Road
Capalaba
Queensland 4157
Australia
Tel: 07 3890 5444
Fax: 07 3890 4777
Email: purchasesau@robus.com
<https://au.robus.com>

Cuthbert Stewart Ltd
22 Fisher Crescent,
Mt Wellington, Auckland.
PO Box 62293, Sylvia Park 1644,
Auckland, New Zealand.
Ph: 0800 288 423
Customer Support:
support@csl-online.nz

