DATASHEETS

COMPACT CLAMP METER TRUE-RMS 600A AC/DC CATIII 600

CAT IV 300V



The Brymen BM079 is a new generation, accurate AC/DC 600A current clamp with numerous features and a very high safety

- 3 5/6 digit, 6000
- CATIII 600V
- True-RMS measurement
- Peak-RMS inrush current 80ms
- AmpTip™ low current range
- EF detection (NCV) and probe contact
- 3 Phase rotation detection (supply and motor)
- · Data hold and relative zero
- Min/Max/Avg recording
- Backlight LCD

- Temp
- Jaws

EΑ QTY 1

| Compliance and Safety | IEC/EN61010-2-032 1st & 3rd Ed. CATIII 600V | |
|-----------------------|---|--|
| Contents | Each BM079 is supplied in a gift box with operating manual, soft carry bag, batteries, thermocouple with plug and test leads. | |
| Dimensions | L223 × W76 × T37mm | |
| Batteries | 2 x 1.5 AA size | |
| Weight | 234g | |
| Spare Leads | AL04RBY Set of 3 leads, red white black with crocodile clips and safety covers, CATIV 1kV (CATII1kV without cover). Crocodile Clips | |

| Diode test APO idle after 32 minutes Temperature type-K thermocouple Jaws 35mm cable with AmpTip™ facility | without cover). Cro rates CATIV600V. |
|---|---|
| | |

| Feature | Range | Accuracy |
|--------------------|-----------------------------------|--------------------|
| AC Current | 60.00A, 600.0A | ±2% + 5 (+10 < 9A) |
| DC Current | 60.00A, 600.0A (50 – 100Hz) | ±2% + 5 (+10 < 9A) |
| AC+DC Current | 60.00A, ^00.0A (50Hz – 100 Hz) | ±2% + 7 |
| AmpTip™ Current | 60.0A AC (50Hz – 100Hz) | ±1.5% + 5 |
| | 60.0A DC | ±2.0% + 5 |
| | 60.00A ACA+DCA (DC, 50Hz – 100Hz) | ±2.2% + 7 |
| DC Voltage | 600.0V | ±1% + 5 |
| AC Voltage | 600.0V @ 50 – 60 Hz | ±1.2%+ 7 |
| AC+DC Voltage | 600.0V (DC, 50Hz – 60Hz) | ±1.2% + 7 |
| Resistance | 600.0Ω, 6.000kΩ, 60.00kΩ | ±1% + 5 |
| Capacitance | 200.0μF, 2500μF | ±2% + 4 |
| Temperature | -40.0° to 99.9° C | ±1% + 0.8° C |
| | 100° to 400° C | ±1% + 1° C |
| DCμA | 200.0μΑ, 2000μΑ | ±1% + 5 |
| | (Burden Voltage +3.5mV/µA) | |
| Frequency | 600V (5Hz – 999.9Hz) | ±1% + 5 |
| | 60A AmpTip™ (50Hz – 400 Hz) | |
| | 60A, 600A (50Hz – 400Hz) | |
| EF-Detection (NCV) | Range (Tolerance) | LCD Bar Indication |
| | 20V (10V – 36V) | - |
| | 55V (23V – 83V) | |
| | 110V (59V – 165V) | |
| | 220V (124V – 330V) | |
| | 440V (250V – 600V) | |

In support of our policy of continuous product improvement we reserve the right to change materials and specifications without notice. Drawings, where used, are not to scale. All dimensions are in millimetres and sizes given are approximate. Where possible, technical MSDS data sheets are made available on the website. All products should be installed and used in accordance with manufacturer's instructions provided. Warning: products may be the subject of registered designs and patents. Refer to website for terms and conditions on warranty.

